

2/PRTS

2, ~~Description~~ I Claim as my Invention:

Method for data transmission in a mobile radio system,
mobile station and base station

5

The invention relates to a base station, a mobile station and a method for data transmission in a communication system, in particular in a CDMA mobile radio system, where the data, structured in frames, are transmitted such that a mobile station is able to perform other functions, in particular to carry out tests using a reception device, during one or more interruption phases in which it interrupts the reception (of the previous source or of the data from the base station) and/or the processing of received data or sending. "Transmission" is also understood to mean sending and/or receiving below.

In communication systems, data (for example voice data, image data or system data) are transmitted on transmission links between base stations and mobile stations. In radio communication systems, this is done using electromagnetic waves via an air or radio interface. In this context, carrier frequencies are used which are situated in the frequency band provided for the respective system. In the case of the GSM (Global System for Mobile Communication), the carrier frequencies are in the range of 900 MHz. For future radio communication systems, for example the UMTS (Universal Mobile Telecommunication System) or other third generation systems, frequencies in the frequency band of 2000 MHz are provided.

Particularly in future CDMA systems, a base station sends continuously, in essence, in the downlink direction, for example, that is to say in the direction from the base station to a mobile station. The data transmitted during sending are usually structured in frames which

Foreign version

each have a prescribed length. Particularly with different services such as voice data transmission and video data transmission, the frames may also have different structures and lengths. The structure and/or
5 length of each frame in a continuous series of frames is prescribed and/or is recognized by the mobile station, however.

Particularly in cellular mobile radio systems, the mobile station occasionally also needs to perform
10 functions other than data reception which cannot be performed at the same time, at least during the operation of only a single reception device. By way of example, from time to time the mobile station in a radio communication system of cellular design in which
15 the base stations in various cells send on different frequencies needs to test whether it is able to receive radio signals from another base station with good reception quality. For this purpose, the mobile station sets its reception device to a frequency other than the
20 frequency on which it currently receives data.

In order to be able to send from the base station to the mobile station without interruption, it has already been proposed that the mobile station be equipped with a second reception device. In practice,
25 however, this solution is usually rejected for cost reasons.

Another proposal is known according to which the base station interrupts sending at prescribed times in order to allow the receiving station to carry out an
30 adjacent channel search (search for an adjacent base station or for particular data packets transmitted by these base stations, where data packets may also be understood below to mean synchronization, frequency correction or pilot signal bursts) using its individual
35 reception device.

GR 98 P 4738

- 2a -

Foreign version

To prevent a loss of data, the base station
sends the data beforehand at a higher transmission rate
than the

0983479 090401

GR 98 P 4738 Foreign version

DE 009903484

- 3 -

fundamentally constant permanent transmission rate. So that this does not result in higher bit error rates (BER), the transmission power additionally needs to be increased during this time.

5 The frequency at which the interruption phases recur and the length of the interruption phases depend on the particular system and also on the particular operating state of the system. By way of example, interruption phases each having a length of 5 to 6 ms,
10 respectively, are sufficient for an adjacent channel search by a mobile station in a radio communication system organized on a cellular basis. WO-A-97 25827 discloses a method for data transmission, in which interruption phases for observing an adjacent base
15 station are inserted during transmission. However, provision is made in this case for the interruption phases to be inserted at regular intervals, which entails the disadvantage that the efficiency of the data transmission is reduced with each interruption
20 phase.

Since the losses in transmission quality also increase with the number of interruption phases inserted, it is desirable for the smallest possible number of interruption phases to be inserted.

25 By way of example, a GSM frame transmitted by the GSM base station contains eight timeslots which each contain a data packet. The data packets transmitted by the GSM base station BS2, such as synchronization data packets (data packets to be
30 detected, synchronization burst), frequency correction data packets (characteristic data packets, frequency correction burst) and normal data packets, are all subordinate to the same time frame. The GSM base stations transmit all 10 time frames (GSM frames) 4
35 times and, after a subsequent 11 time frames (GSM frames) (51 time frames in total), a frequency

AMENDED SHEET

03-11-2000

GR 98 P 4738 Foreign version

DE 009903484

- 3a -

correction data packet, and one respective time frame
later, a synchronization data packet.

09949.03049

AMENDED SHEET

If interruption phases based on the GSM standard were now inserted with a period of 26 time frames (GSM frames), the fact that the period of 51 time frames and the period of 26 time frames have no common denominator would cause a cyclic shift in the two time frame periods, so that after a maximum of 11 times 26 time frames, that is to say after 11 observation frames, the sought data packet which is to be detected would be received if the mobile station is not too distant from the respective adjacent base station BS2, BS3 or if no interference which is too intense arises during transmission.

It is an object of the present invention to specify a method for data transmission, a mobile station and a base station which permit second base stations to be reliably observed while transmission quality is good.

The object is achieved by the independent patent claims. Developments are the subject matter of the dependent claims.

Accordingly, the invention is based, in particular, on the concept of, contrary to the prior art, inserting interruption phases in which the mobile station interrupts the transmission, in particular the reception, of the data sent by the first base station and/or the processing of the received data not with a maximum effective total duration which would be needed under optimum transmission conditions for secure detection of a data packet which is to be detected, but instead inserting fewer and/or shorter interruption phases.

Complex simulations using simulation tools developed specially for this purpose have proved that, when the effective total duration of the interruption phases is shortened, contrary to the prior art, to a duration of a maximum of 9 or a maximum of 10

03-11-2000

GR 98 P 4738 Foreign Version

DE 00990348

- 4a -

observation frames, the effective total duration of the
interruption phases can be reduced

03-11-2000

AMENDED SHEET

by a much greater proportion than, in return, the theoretical detection probability for a data packet which is to be detected decreases. The effect of this is that the transmission quality from the first base station to a mobile station is improved, but in return the detection probability for a data packet which is to be detected remains comparatively high with respect thereto.

In this case, the data can be sent, by way of example, from the first base station to the mobile station, in which case, at least during particular transmission phases, interruption phases are inserted in which the first base station interrupts sending, and the mobile station interrupts the reception and/or the processing of received data, for example, and in which the mobile station is switched to the reception of the characteristic data packets and/or data packets which are to be detected, which are sent cyclically by a second base station, and the maximum effective total duration of the interruption phases is shorter than would be needed under optimum transmission conditions for secure detection of a data packet which is to be detected.

The data packets sent by the second base station may also be data packets which are to be detected (synchronization data packets) or characteristic data packets (frequency correction data packets).

In this context, a first transmission method, used by a first base station, may be a CDMA method, and a second transmission method, used by a second base station, may be a GSM method.

Within the context of the application, GSM frame is also understood to mean a frame which contains 8 time slots and has a duration of 4.6 ms.

- 5a -

Within the context of the application, observation frame is also understood to mean a minimum time period required in order to observe a GSM frame. In this case, the exact duration of an observation
5 frame is implementation-dependent; however, in order to ensure full detection of a GSM frame and to allow for the time needed for changing over the synthesizer frequency, it is generally longer than the duration of a GSM frame and may thus also have a duration of 9 time
10 slots, 10 time slots (5.7 ms), 11 time slots or 12 time slots (6.9 ms).

Since many different variants are possible for inserting the interruption phases for the purpose of the adjacent channel search, the term "maximum
15 effective total duration of the interruption phases" within the context of this application denotes the sum of all the interruption phases inserted as a maximum in order to observe an adjacent base station. However, this does not preclude further interruption phases from
20 being inserted during subsequent repetition of the adjacent channel search, although a new effective total duration of the interruption phases is formed in this case. Under these circumstances, the individual interruption phases may each have the duration of an
25 observation frame, but may also have any other duration. The duration of an interruption phase may also have a multiple or a fraction of the duration of an observation frame. It is also possible for the individual interruption phases to have different
30 durations.

In one development of the invention, a period of 52 GSM frames lies between the start of a first interruption phase and the start of a second interruption phase.

35 Simulations have been able to show that this allows the effective total duration of the

AMENDED SHEET

03-11-2000

GR 98 P 4738 Foreign Version

DE 00990348

- 5b -

interruption phases to be reduced to 91%, with a mere loss of 2% needing to be accepted for the detection probability in return, as well as a halving of the search speed in comparison with the GSM search speed.

- 5 In another embodiment of the invention, a period of 6 GSM frames is inserted between the start of a first interruption phase and the start of a second interruption phase, and a period of 46 GSM frames is

03-11-2000

inserted between the start of a second interruption phase and the start of a third interruption phase.

In this case, simulations have been able to show that, at GSM search speed, the maximum effective
5 total duration of the interruption phases can be reduced by 9% for a comparatively very small detection possibility loss of 2%.

In one development of the invention, the insertion of further interruption phases is ended,
10 restricted or continued under control before the maximum effective total duration of the interruption phases is actually reached. To this end, after reception of a data packet which is to be detected or possibly of another data packet, indicating the end of
15 the adjacent channel search, such as a characteristic data packet, an appropriate message is transmitted from the mobile station to the first base station.

Thus, while data are transmitted from a first base station to a mobile station in the downlink
20 direction, for example, interruption phases are inserted, at least during particular send phases, in which the mobile station interrupts the reception of the data sent by the first base station and/or the processing of the received data and in which the mobile
25 station is switched to the reception of data packets sent by a second base station. Depending on a reception result for these data packets sent by a second base station, information which influences the insertion of interruption phases is sent from the mobile station to
30 the first base station.

In this way, it is possible for the insertion of interruption phases to be ended as soon as possible, and hence to be restricted as far as possible, as soon as sufficient information is known about the second
35 base stations which are to be observed, and hence for the transmission

0983179 030401

quality to be improved. The effect of this is that the total duration of the interruption phases can be reduced further.

5 The drawings are now used to describe exemplary embodiments of the invention in more detail. The invention is not limited to these exemplary embodiments, however. In the individual figures of the drawing:

10 Figure 1 shows a basic circuit diagram of a mobile radio system;

Figure 2 shows a basic circuit diagram of a mobile station;

15 Figure 3 shows a schematic illustration of the insertion of interruption phases during a send phase.

20 Figure 1 shows a cellular mobile radio network comprising, by way of example, a combination of a GSM (Global System for Mobile Communication) system with a UMTS (Universal Mobile Telecommunication System) system, which comprises a multiplicity of mobile switching centers MSC which are interlinked and set up access to a landline network PSTN/ISDN. In addition, these mobile switching centers MSC are connected to at least one respective base station controller BSC, which
25 may also be formed by a data processing system.

Each base station controller BSC is in turn connected to at least one base station BS. Such a base station BS is a radio station which is able to use a radio interface to set up a radio link to other radio
30 stations, so-called mobile stations MS. Radio signals can be used to transmit information between the mobile stations MS and the base station BS associated with these mobile stations MS within radio channels situated within frequency bands. The range of the radio signals
35 of a base station defines, in essence, a radio cell FZ.

Base stations BS and a base station controller BSC can be combined to form a base station system. In this context, the base station system BSS is also responsible for radio channel administration and allocation, data rate matching, monitoring of the radio transmission link, handover procedures and, in the case of a CDMA system, for the allocation of the spread code sets which are to be used, and transmits the signaling information required for this to the mobile stations MS.

In the case of a duplex system, the frequency bands provided for the uplink (mobile station to base station) may be different than those provided for the downlink (base station to mobile station) in FDD (Frequency Division Duplex) systems, such as the GSM system, and, in TDD (Time Division Duplex) systems, such as the DECT (Digital Enhanced Cordless Telecommunications) system, different time intervals may be provided for the uplink and for the downlink. Within the different frequency bands, an FDMA (Frequency Division Multiple Access) method can implement a plurality of frequency channels.

Terms and examples used within the context of this application also often refer to a GSM mobile radio system; they are in no way limited thereto, however, but rather may also easily be mapped onto other, possibly future, mobile radio systems, such as CDMA systems, in particular wideband CDMA systems or TD/CDMA systems, by a person skilled in the art using the description. First base station BS1 is understood to mean, in particular, a UMTS base station or a CDMA base station, second and/or third base stations BS2, BS3 are understood, in particular, to mean GSM (adjacent) base stations which are to be observed, and mobile station is understood, in particular, to mean a dual mode mobile station designed both for

GR 98 P 4738

- 8a -

Foreign version

receiving/sending GSM signals and for receiving/sending
UMTS signals or CDMA signals, said

0991646044

dual mode mobile station also being able to be made ready for stationary operation, if appropriate.

Figure 2 shows a radio station which may be a mobile station MS, comprising an operating unit MMI, a control device STE, a processing device VE, a power supply device SVE, a reception device EE and a transmission device SE.

The control device STE in essence comprises a program controlled microcontroller MC which has write and read access to memory modules SPE. The microcontroller MC controls and supervises all the fundamental elements and functions of the radio station, in essence controls the communication and signaling flow, reacts to keypad inputs by executing the corresponding control procedures and is also responsible for transferring the appliance into different operating states.

The processing device VE can also be formed by a digital signal processor DSP which is likewise able to access memory modules SPE.

The volatile or nonvolatile memory modules SPE store the program data required for controlling the radio station and the communication flow, and also the signaling procedures in particular, appliance information, information entered by the user and information arising during the processing of signals.

The radiofrequency part HF comprises the transmission device SE, having a modulator and an amplifier, and a reception device EE having a demodulator and likewise an amplifier.

The transmission device SE and the reception device EE are supplied with the frequency of a voltage controlled oscillator VCO

Foreign version

using the synthesizer SYN. The voltage controlled oscillator VCO can also be used to generate the system clock for clocking processor devices of the appliance.

For receiving and sending signals via the air
5 interface of a mobile radio system, an antenna device
ANT is provided.

The radio station may also be a base station BS. In this case, the operating unit is replaced by a link to a mobile radio network, for example by means of a base station controller BSC or a switching center MSC. In order to interchange data with a plurality of mobile stations MS at the same time, the base station BS has an appropriate multiplicity of transmission and reception devices available.

15 Figure 3 shows the frame structure of a data
transmission with a short delay time, in particular of
voice transmission in a UMTS (Universal Mobile
Telecommunication System), containing twelve individual
frames 1 for data transmission within a respective
20 multiframe. In this case, the illustration shows, in
particular, a send phase in the downlink from a first
base station BS1, in particular a UMTS base station
BS1, to a mobile station MS, in particular a dual mode
mobile station MS, designed not only for receiving UMTS
25 data but also for receiving GSM data packets. The
statements employed below are, in essence, restricted
to the downlink. It goes without saying, however, that
the invention can be introduced not only to downlink
transmission, but also to uplink transmission. It is
30 within the scope of action of a person skilled in the
art to introduce the exemplary embodiments demonstrated
below for the downlink to uplink transmission.

The individual frames 1 each have a transmission length T_f of 10 ms, which means that the mutliframe has a transmission length T_s of 120 ms in total. The respective fifth and sixth individual

THE JOURNAL OF THE

frames 1 have a common interruption phase 2 (possibly overlapping their frame boundaries 3) which has a length T_i . The length T_i is 6 ms, for example. The subsections of the first frame 4a, which starts before the interruption phase 2, and of the second frame 4b, which ends after the interruption phase 2, are of the same length or of the same size. In the case of the exemplary embodiment shown in figure 3, voice data are being transmitted, so that a maximum delay of 10 ms, that is to say a frame length T_f , when evaluating the data received by the mobile station is acceptable. The data within a frame are sorted, coded together and sent superimposed on one another. In the exemplary embodiment, the transmission rate of the first frame 4a and of the second frame 4b is increased in each case such that the same quantity of information which is to be sent, which is sent in uncompressed frames 1 over the frame length T_f , is sent in a time span $T_c = T_f - T_i/2$.

In this case, during the interruption phases, at least the sending of data to a particular mobile station carrying out the adjacent channel search is interrupted, while sending to other mobile stations can be continued, this being made possible by the use of a multiple access method, for example a CDMA method.

A GSM frame transmitted by the GSM base station contains eight timeslots which each contain a data packet. The data packets transmitted by the GSM base station BS2, such as synchronization data packets (data packets to be detected, synchronization burst), frequency correction data packets (characteristic data packets, frequency correction burst) and normal data packets, are all subordinate to the same time frame. The GSM base stations transmit all 10 time frames (GSM frames) 4 times and, after a subsequent 11 time frames (GSM frames) (51 time frames in total), a frequency correction

data packet, and one respective time frame later, a synchronization data packet.

If interruption phases based on the GSM standard were now inserted with a period of 26 time frames (GSM frames), the fact that the period of 51 time frames and the period of 26 time frames have no common denominator would cause a cyclic shift in the two time frame periods, so that after a maximum of 11 times 26 time frames, that is to say after 11 observation frames, the sought data packet which is to be detected would be received if the mobile station is not too distant from the respective adjacent base station BS2, BS3 or if no interference which is too intense arises during transmission.

If the maximum effective total duration of the interruption phases is now reduced, contrary to the prior art, from 11 observation frames to, by way of example, 10 or 9 observation frames when observing GSM base stations during the call phase for a mobile station MS and a UMTS base station BS1, the data transmission within the context of the call by the mobile station MS via the base station BS1 can be improved. The associated reduction in detection probability is comparatively small and is thus acceptable.

In one variant embodiment of the invention, data packets which are to be detected are transmitted by a second base station BS2 within GSM frames, and interruption phases for adjacent channel observation are inserted into the downlink data transmission from a UMTS base station BS1 to a mobile station MS, with a period of 52 GSM frames lying between the start of a first interruption phase and a second interruption phase.

In another variant embodiment, a period of 26 GSM frames lies between the start of a first interruption phase and a second interruption phase.

In another embodiment of the invention, a
5 period of n1 GSM frames lies between the start of a first interruption phase and a second interruption phase, and a period of n2 GSM frames lies between the start of a second interruption phase and a third interruption phase.

10 In another variant embodiment of the invention, a period of 6 GSM frames lies between the start of a first interruption phase and a second interruption phase, and a period of 46 GSM frames lies between the start of a second interruption phase and a third
15 interruption phase.

In another variant embodiment of the invention, a period of 16 GSM frames lies between the start of a first interruption phase and a second interruption phase, and a period of 36 GSM frames lies between the
20 start of a second interruption phase and a third interruption phase.

By way of example, while the mobile station MS is in the call condition or user data transmission condition with a current UMTS base station BS1, the
25 interruption phases are inserted at particular points in time/intervals of time, between which there may be time spans of fixed or different length, into the downlink transmission, during which the reception device of the mobile station MS is switched to the
30 reception of data packets from respective adjacent GSM base stations BS2, BS3. During the interruption phase 2, the UMTS base station thus interrupts the sending of data to the mobile station MS, and the mobile station MS interrupts the reception and/or the processing of
35 data sent by the

UMTS base station BS1. The mobile station MS uses the reception device EE to carry out an adjacent channel search by virtue of the control device STE switching the reception device EE to the reception of adjacent
5 GSM base stations BS2 and of the data packets sent thereby, in order to receive any synchronization data packets dp which arrive, sent by adjacent GSM base stations BS2, BS3.

The aim of the adjacent channel search is also
10 to detect a synchronization data packet which is to be detected. In one variant embodiment of the invention, if, in one of these interruption phases, the mobile station MS receives a synchronization data packet which is to be detected, then the adjacent channel search has
15 ended, at least for this base station BS2, and the mobile station MS sends appropriate control information m (SCH-found) to the first base station BS1, the UMTS base station, possibly via suitable signaling channels. The UMTS base station BS1 then inserts no further
20 interruption phases into the downlink data stream d, at least at first. In this case, the effective total duration of the interruption phases is generally shorter than the maximum effective total duration of the interruption phases.

A synchronization data packet which is to be
25 detected can also be detected using the reception of a characteristic frequency correction data packet, since the known frame structure after reception of a frequency correction data packet means that the
30 position of a synchronization data packet is known. Since, in the GSM system, the base stations BS2, BS3 transmit the frequency correction data packets one time frame before the synchronization data packets, in one variant embodiment of the invention, the mobile station
35 MS is able not only to receive synchronization data packets but also to be switched to the reception of frequency correction data packets. In this case, the

0963479 000404

Foreign version

mobile station MS carries out an adjacent channel
search in the interruption phases using

09047380000

the reception device EE, by virtue of the control device STE switching the reception device EE to the reception of adjacent GSM base stations BS2, in order to receive any synchronization data packets and
5 frequency correction data packets which arrive, sent by adjacent GSM base stations BS2, BS3.

Within the context of this application, the concept of "the mobile station being switched to the reception of data packets which are to be detected
10 and/or characteristic data packets" is also understood to mean that, after the customary analog and digital filtering, and possibly derotation, the received data packet is compared (e.g. correlated) with the correlation series corresponding to the training
15 sequence of a characteristic data packet dp and/or with the correlation series corresponding to the training sequence of a data packet dp which is to be detected, and hence data packets which are to be detected and characteristic data packets are sought at the same time or in parallel. Instead of correlation, other methods
20 may also be used if appropriate (e.g. FIR, IRR or other filters). If a data packet is received or detected with sufficient quality, or the information transported using the data packet is ascertained with sufficient
25 quality etc., the reception result for this data packet can be said to be positive.

In one variant embodiment, the mobile station MS is now able, after reception of a frequency correction data packet, to send information m to the
30 UMTS base station BS1 (FCCH-found), which information now causes just one further interruption phase to be inserted into the sent data stream at first, in order to receive the synchronization data packet following the frequency correction data packet at a fixed
35 distance. The knowledge about the relative positions in time of the frequency correction data packet and the synchronization data packet means that the position in

03934738-0000

Foreign version

time and also the duration (since the timeslot is now known) of the interruption phase which is to be inserted can be matched to the position in time of the synchronization data packet which is to be

09034738 "090401

detected. Corresponding information about the position in time of a frequency correction data packet or of a following synchronization data packet can be transmitted with the FCCH-found message.

5 In another variant embodiment of the invention, the mobile station is first switched to the observation of a first adjacent GSM base station BS2, after a successful search or on the basis of knowledge about an unsuccessful search the adjacent channel search is
10 carried out for one or more further GSM base stations BS3, and when the adjacent channel search for a plurality of adjacent GSM base stations BS2, BS3 has ended successfully and/or without success, information m for influencing and/or restricting and/or ending
15 and/or controlled continuation of the insertion of interruption phases is transmitted to the UMTS base station BS1. To this end, the initially ascertained results for the adjacent channel search can be temporarily stored using memory devices SPE in the
20 mobile station MS.

In one embodiment of the invention, if no adjacent channel search is successful, this is signaled, likewise using appropriate information m (FCCH/SCH-not-found), and the UMTS base station inserts
25 no further interruption phases into the downlink data stream d at first.

In one development of the invention, the results of the adjacent channel search, for example the identity of the adjacent base station and the reception
30 quality or field strength of the signals received from the adjacent base stations, are transmitted to the UMTS base station BS1 together with the information for influencing the insertion of interruption phases as one message, which may be split over a plurality of frames
35 if appropriate.

033496901

Reference

Reference